


# Series 80 "Mighty Mouse" Filter Connector Contact Arrangements




The contact arrangements on this page apply to filtered versions of Series 801, 804 and 805 only. The size #23 contacts are rated at 5 amps current and accept #22 to #28 AWG wire.


## Mating Face View of Pin Insert, Socket Cavity Numbers are Reversed



Series 801	5-3	6-1	6-4	6-7	7-1	7-10	8-13
Series 804	5-3	6-1	6-4	6-7	7-1	7-10	8-13
Series 805	Not Avail.	8-1	8-4	8-7	9-1	9-10	10-13
Number of Contacts	3	1	4	7	1	10	13
Contact Size	#23	#16	#23	#23	#12	#23	#23



Series 801	9-4	9-19	10-26	13-2
Series 804	9-4	9-19	10-26	12-2
Series 805	11-4	11-19	12-26	15-2
Number of Contacts	4	19	26	2
Contact Size	#16	#23	#23	#12



Series 801	13-37	16-55	17-85
Series 804	12-37	14-55	15-85
Series 805	15-37	18-55	19-85
Number of Contacts	37	55	85
Contact Size	#23	#23	#23