SERIES 880





Shell Size and	d Insert <i>I</i>	Arrange	ments			
	No. of Contacts					
Insert Arrangement	#23 5A.	Micro 3A.	Nano 1A.			
B7N	—	—	7			
C10N	—	_	10			
C2M2N	_	2	2			
D3M	—	3	_			
D2W2N	2	_	2			
E3W	3	_	_			
E4M	—	4				
E19N	—	_	19			
E4M4N	_	4	4			
F4W	4	_	_			
F7M	_	7	_			
F22N	—	_	22			
F4M8N	_	4	8			
F4W4N	4	—	4			
G7W	7	—	—			
G10M	_	10	_			
G31N	—	—	31			
G6M10N	—	6	10			
G6M12N	—	6	12			
H10W	10	—	—			
H37N	—	—	37			
H6W14N	6	_	14			
J44N	—	—	44			
J7W19N	7	_	19			
K19M	—	19	_			
K13M19N	—	13	19			
L22M	_	22	_			

First letter of insert arrangement represents connector shell size, as in this example: K13M19N

NOTES

- 1. See Section A for insert arrangement layouts
- 2. See Section A for additional finish options

Quick Disconnect



880-002R Cable Receptacle with Pigtail Wires and Integral Banding Porch


Series 880 Quick-Disconnect (QDC) cable receptacles are pre-wired and sealed with epoxy. In-line receptacle has integral shield termination platform and Three contact sizes are available with current ratings of 5A, 3A and 1A. Aluminum or stainless steel housings and thermoplastic insulators. High-strength wire with crosslinked ETFE insulation crimped at factory to high performance contacts. Ultraminiature SuperFly[®] connectors are ideal for soldier systems and other applications where reduced size and weight are critical.

How To Order									
Sample Part Number		er 880-002R		-B7N	-M	004	J	1	-24
Series	880-002	R							
Insert Style	B = Shrou Shrouded	A = Unshrouded Contacts B = Shrouded Contacts Shrouded contacts are recessed within the insulator							
Shell Size/ Insert Arr.1	bee biieii	See Shell Size and Insert Arrangement Table							
Material/ Finish²	M = Aluminum/electroless nickel RoHS compliant ZR = Aluminum/zinc-nickel, non-reflective with RoHS compliant black chromate MT = Aluminum/nickel-PTFE RoHS compliant ZMT = Stainless steel/nickel-PTFE RoHS compliant								
Wire AWG	See Wire Code Table								
Wire Type	J = "Space Grade" wire M22759/33 or equivalent (ETFE)								
Wire Color	1 = White 5 = Full Color; 1-10 solid color, 11 and up are striped 7 = 10 Color Repeating; Wire #1 black, Wire #11 black, etc								
Wire Length	Overall length ('L') in inches measured from front of connector								

MOD-686 POLARIZING OPTIONS

Standard SuperFly[®] connectors have a single master key. Versions with three keys are also available if alternate key positions are required. Add suffix code 686 to the part number per the following example: 880-002RA-B7N-M004J1-24-**686A**

Plug Alternate Key Positions							
Suffix Code	A°	B°					
686A	150°	210°					
686B	75°	210°					
686C	95°	230°					
686D	140°	275°					
686E	75°	275°					
686F	95°	210°					



SERIES 880

Quick Disconnect



880-002R Cable Receptacle with Pigtail Wires and Integral Banding Porch

ABOUT SHROUDED AND UNSHROUDED SUPERFLY® CONFIGURATIONS

Shrouded contacts are recessed within the insert. Unshrouded contacts extend from the insert face. Shrouded inserts contain 1 amp and 3 amp Twistpin contacts along with 5 amp socket contacts. Unshrouded inserts contain 1 amp and 3 amp sockets and 5 amp pin.

		e Table						3 Amp Micro Tw	istpin		
Layouts with 5A.	Conta #23	cts Micro	Nano		Shrouded			1 Amp			
Arrangement	#25 5A.	3A.	1A.	Code	Type B Insert			Nano Twi	istpin		
	#22	_	_	100				5 Amp			
E3W, F4W,	#24	_	_	200			111111	#23 Sock	ket		
G7W, H10W	#26	_	_	300							
Layouts with 5A.	and 1/	A. Conta	acts								
Insert	#23	Micro	Nano	Cada							
Arrangement	5A.	3A.	1A.	Code		1///		3 Amp Micro Se	ookot		
	#22		#28	104					UCKEI		
	#24		#28	204	Unshrouded			1 Amp			
	#26		#28	304	Type A Insert			Nano S	Socket		
D2W2N, F4W4N,	#22		#30	105				5 Amp			
16W14N, #24			#30	205				#23 Pin	#23 Pin		
J7W19N #26		#30	305								
	#22		#32	106							
	#24		#32	206							
	#26	—	#32	306							
Layouts with 3A.	Conta	cts									
Insert	#23	Micro	Nano	Code		00 (+25.4/00					
Arrangement	5A.	3A.	1A.		.806 (20.47) —	4					
D3M, E4M F7M,	_	#24	_	020	.313 (7.95) —	∕−ØA					
G10M, K19M,	#26	—	030								
L22M — #2	#28	—	040								
		#30	—	050							
Layouts with 3A.		1			4	┨_┵┤ ││					
Insert Arrangement	#23 5A.	Micro 3A.	Nano 1A.	Code				\smile			
Arrangement 5A		#24	#28	024	[∠] Pigtail Wires		r [®] Nano Band Sh	hield			
		#24	#28	024		Termination	Platform				
	_	#20	#28	044		- •					
C2M2N,	_	#24	#30	025		1	ensions				
E4M4N, F4M8N G6M10N,		#26	#30	035	Shell Size		MAX	Ø			
G6M12N,	_	#28	#30	045		In.	mm.	In.	mm.		
K13M19N	_	#24	#32	026	В	.317	8.05	.197	5.00		
		#26	#32	036	С	.342	8.69	.222	5.64		
		#28	#32	046	D	.355	9.02	.235	5.97		
Layouts with 1A.	Conta		"JZ	040	E	.381	9.68	.261	6.63		
Insert	#23	Micro	Nano		F	.400	10.16	.280	7.11		
Arrangement	π25 5A.	3A.	1A.	Code	G	.422	10.72	.302	7.67		
B7N, C10N,	_	_	#28	004	Н	.459	11.66	.339	8.61		
E19N, F22N,	—	_	#30	005	J	.487	12.37	.369	9.37		
G31N, H37N,		_	#32	006	К	.509	12.93	.391	9.93		
J44N	_		πJZ	000	L	.548	13.92	.430	10.92		